



## JR-1000

### Single-Channel Temperature Data Logger

The JR-1000 is the easiest to use temperature data logger available. With its precision calibrated internal temperature sensor, simply place the logger in the field and leave it to record. Once the desired information has been recorded, plug the logger into the serial port of your computer and begin downloading and viewing the logged data with ACR's TrendReader® 2 Express software or feature filled TrendReader® 2 software.

#### APPLICATIONS

Food process verification, pharmaceutical storage, laboratories, transportation of temperature sensitive goods, equipment run time, HVAC system testing and balancing etc.

#### GENERAL SPECIFICATIONS

Size:	33mm x 43mm x 20mm (1.3" x 1.7" x 0.75")
Weight:	35 g (1.23 oz)
Case Material:	Polyurethane
Battery:	3.6 volt Lithium, 0.45 Amp-Hour
Resolution:	8-bit (1 part in 256)
Mounting:	Magnetic backing
Clock Accuracy:	± 2 seconds per day
Sampling Methods:	First-in First-out, Stop When Full, Delay Start, or Spot & Average
Operating Limits:	-40°C to 85°C (-40°F to 185°F) and 0 to 95% RH (non-condensing)
PC Requirements:	Windows PC with at least one free USB or serial port (depending on connection)
Software Requirements:	TrendReader® 2 Express or TrendReader® 2 (Compatible with Windows XP, Vista, Windows 7 and Windows 8 [32 bit & 64 bit])
Memory Size:	32 KB (capable of storing up to 244,800 readings when data compression is selected)
Sampling Rates:	User selectable rates from 8 seconds to 34 minutes (readings stored to memory can be spot or averaged over the sample interval, except for the 8-second interval)
Number of Channels:	One (one internal channel for ambient temperature)



#### SENSOR SPECIFICATIONS

Temperature Sensor Type:	NTC Thermistor - 10,000 Ohms @ 25°C (77°F)
Range:	-40°C to 85°C (-40°F to 185°F)
Accuracy:	±0.2° over the range of 0°C to 70°C (±0.3°C over the range of 32°F to 158°F)
Resolution:	0.4°C (0.7°F) @ 25°C; better than 1°C (1.8°F) between -25°C and 70°C (-13°F and 158°F); better than 2.0°C (3.6°F) between -40°C and -25°C (-40°F and -13°F)

#### ORDERING INFORMATION

Item	Cat#:
JR-1000-SP Starter Pack*	01-0192
JR-1000 (Data Logger Only)	01-0196

\*Starter Pack includes:  
One JR-1000 Data Logger  
TrendReader® 2 Express Software CD  
Serial to USB adapter cable  
Quick Start Guide



ACR Systems Inc  
Toll-Free: 1.800.663.7845  
Tel: 1.604.591.1128  
sales@acrsystems.com

[www.acrsystems.com](http://www.acrsystems.com)

ISO 9001 Certified

ISO9000\SPECIFICATIONS\JR-1000.pdf



Rev:10 - 10/24/12